

Casambi to DMX Controller



The Casambi to DMX Controller is a Bluetooth-enabled device that allows any DMX driver or fixture to operate with Casambi. This controller can manage up to eight DMX channels, making it an excellent choice for RGBW and tunable white (TW) applications.

The controller can be configured for various output types, including 4-channel RGBW (color picker), 4 individual channels, and 8 individual channels. It can be managed using the Casambi app, which is available for free download from the Apple App Store and Google Play Store.

Casambi to DMX Controller

- For indoor and outdoor use
- Bluetooth controllable
- Casambi Enabled 8-Channel DMX Master
- Multiple Casambi profiles
- Managed via the Casambi app.

IP 65

Casambi to DMX Controller



Supply voltage (mains)	100-240V 50/60Hz
Power consumption	1 W
Output	DMX
DMX channel	Up to 8 individual channels
Systems applicable	Casambi Bluetooth Control
Dimensions	95 x 65 x 60 mm
Ambient temperature	-20° C to 45° C
Protection rating	IP 65

Item no.

Casambi to DMX Controller

8000 0031